

ACTUADOR DE PERSIANA REGULABLE Y ORIENTABLE

Up or down any shutter, blinds or screens from the switch or remote control.

Specifications

Power Supply	100-240V~ 50/60 Hz
Rated load current	4.2A for lamps and resistive loads 1.7A for motors with compensated power factor (inductive loads)
Supported motor type	single-phase AC motors
Required limit switches	electronic or mechanic
Power consumption	up to 0.8W
Operating temperature	0-35°C
Operating humidity	10-95% RH without condensation
Active element	micro-gap relay switch μ
For installation in boxes	$\varnothing \geq 50\text{mm}$, depth $\geq 60\text{mm}$
Radio protocol	Z-Wave (500 series chip)
Radio signal power	EIRP up to 6dBm
Radio frequency	868.4 or 869.8 MHz EU; 908.4 or 916.0 MHz US; 921.4 or 919.8 MHz ANZ; 869.0 MHz RU;
Range	up to 50m outdoors up to 40m indoors (depending on terrain and building structure)
Dimensions (L x W x H)	42.5 x 38.25 x 20.3 mm
Compliance with EU directives	RoHS 2011/65/EU RED 2014/53/EU